



BSI Standards Publication

**Integration of internal arc-fault mitigation systems
in power switchgear and controlgear assemblies
(PSC assemblies) according to IEC 61439-2**

National foreword

This Published Document is the UK implementation of IEC TS 63107:2020.

The UK participation in its preparation was entrusted to Technical Committee PEL/121/2, Low voltage switchgear and controlgear assemblies.

A list of organizations represented on this committee can be obtained on request to its secretary.

This publication does not purport to include all the necessary provisions of a contract. Users are responsible for its correct application.

© The British Standards Institution 2020
Published by BSI Standards Limited 2020

ISBN 978 0 580 97397 0

ICS 29.130.20

Compliance with a British Standard cannot confer immunity from legal obligations.

This Published Document was published under the authority of the Standards Policy and Strategy Committee on 31 May 2020.

Amendments/corrigenda issued since publication

Date	Text affected
------	---------------



TECHNICAL SPECIFICATION

SPECIFICATION TECHNIQUE



Integration of internal arc-fault mitigation systems in power switchgear and controlgear assemblies (PSC assemblies) according to IEC 61439-2

Intégration de systèmes de limitation de défaut d'arc interne dans des ensembles d'appareillage de puissance (EAP) conformément à l'IEC 61439-2

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

COMMISSION
ELECTROTECHNIQUE
INTERNATIONALE

ICS 29.130.20

ISBN 978-2-8322-8249-6

**Warning! Make sure that you obtained this publication from an authorized distributor.
Attention! Veuillez vous assurer que vous avez obtenu cette publication via un distributeur agréé.**

CONTENTS

FOREWORD.....	3
INTRODUCTION.....	5
1 Scope.....	7
2 Normative references	7
3 Terms and definitions	8
4 Symbols and abbreviated terms.....	10
5 Interface characteristics.....	10
6 Information	10
7 Service conditions	11
8 Constructional requirements	11
9 Performance requirements.....	12
10 Design verification	13
11 Routine verification.....	22
Annex HH (informative) Guidance for the user of PSC-assemblies about the aspects to be considered when specifying a PSC-assembly with an integrated IAMS.....	24
HH.1 General information.....	24
HH.2 Influence of the electrical parameters of the supply	25
HH.3 Interaction with other devices/systems in the PSC-assembly	26
Annex II (informative) Guidance for the original manufacturer of PSC-assemblies on construction requiring particular attention when incorporating IAMS.....	28
II.1 Selection of devices forming parts of an IAMS	28
II.2 Installation of switching devices and components	28
II.3 Accessibility	29
Annex JJ (informative) Description of the extinction of an internal arc-fault in a PSC-assembly by an IAMS using an AQD during testing.....	30
JJ.1 General	30
JJ.2 Circuit diagram and event description	30
JJ.3 Selected oscillograms	31
Bibliography.....	38
Figure HH.1 – Time/current characteristic curves NH- Fuse-links Size 000 – 3 gG AC 400 V IEC 60269-2	25
Figure JJ.1 – Circuit diagram	30
Figure JJ.2 – Incoming currents at the beginning of the sequence	31
Figure JJ.3 – Currents and voltages at the incoming terminals at the end of the sequence.....	32
Figure JJ.4 – Currents in the AQD circuit	33
Figure JJ.5 – Currents in the arc-fault circuit.....	34
Figure JJ.6 – Currents in the arc-fault circuit, curves magnified	35
Figure JJ.7 – Voltages at the incoming terminals	36
Figure JJ.8 – Electrical energy caused by the arc-fault currents and the voltages at the incoming terminals with t_0 as the start point for calculation	37
Table 1 – Symbols and abbreviated terms	10

INTERNATIONAL ELECTROTECHNICAL COMMISSION

**INTEGRATION OF INTERNAL ARC-FAULT MITIGATION SYSTEMS IN
POWER SWITCHGEAR AND CONTROLGEAR ASSEMBLIES
(PSC-ASSEMBLIES) ACCORDING TO IEC 61439-2**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

The main task of IEC technical committees is to prepare International Standards. In exceptional circumstances, a technical committee may propose the publication of a Technical Specification when

- the required support cannot be obtained for the publication of an International Standard, despite repeated efforts, or
- the subject is still under technical development or where, for any other reason, there is the future but no immediate possibility of an agreement on an International Standard.

Technical specifications are subject to review within three years of publication to decide whether they can be transformed into International Standards.

IEC TS 63107, which is a technical specification, has been prepared by subcommittee 121B: Low-voltage switchgear and controlgear assemblies, of IEC technical committee 121: Switchgear and controlgear and their assemblies for low-voltage.

The text of this technical specification is based on the following documents:

DTS	Report on voting
121B/89/DTS	121B/97/RVDTS

Full information on the voting for the approval of this technical specification can be found in the report on voting indicated in the above table.

This technical specification is to be read in conjunction with IEC 61439-1 and IEC 61439-2. The provisions of IEC 61439-1 and IEC 61439-2 are applicable to this document where they are specifically cited. When this document states "addition", "modification" or "replacement", the relevant text in IEC 61439-1 and IEC 61439-2 is to be adapted accordingly.

This document has been drafted in accordance with the ISO/IEC Directives, Part 2.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC web site under "<http://webstore.iec.ch>" in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

INTRODUCTION

Internal arc-fault mitigation systems (IAMS) denote systems that consist of an internal arc-fault control device (IACD) and an internal arc-fault reduction device (IARD).

An IACD and an IARD can be combined and designed in one device.

An IACD uses the effects of an arc, e.g. light, gas pressure, change of current and/or voltage to detect an arc inside the power switchgear and controlgear assembly (PSC-assembly) to generate a trigger signal for an associated IARD.

An IARD reduces the arc energy below the level which would be released if an IARD was not present and the fault would be interrupted by the conventional short-circuit protective device (SCPD).

The operation of IARDs can be achieved by various methods, individually or in combination including, but not limited to, the following examples:

- a) by interruption using an upstream SCPD triggered by an IACD;
- b) by parallel connection of a low-impedance current path by using an arc quenching device (AQD) for commutation of current to this parallel path. The operation of an upstream SCPD is also required to interrupt the short-circuit current caused by the AQD before it exceeds its current carrying capabilities;
- c) by introducing a defined impedance in series with the arc-fault circuit by using an internal arc-fault limiting device (IALD). An upstream SCPD may be required to extinguish the arc.

The most commonly used techniques are described under a) and b) above.

The purpose of this document is:

- to define the specific requirements for the correct integration of the IAMS into PSC-assemblies which shall be fulfilled by the original manufacturer of the assembly.
- to provide the necessary requirements in order to verify the correct operation of the IAMS.
- to provide the user with details of the different options that can be considered when requiring IAMS within a PSC-assembly.
- to provide guidance to the original manufacturer of PSC-assemblies on the constructional requirements needing particular attention when incorporating the IAMS.

For the safe and reliable operation of the IAMS, the proper operation of the IARD in conjunction with the accompanying IACD is crucial. It is assumed, that passing all tests detailed in this document will verify the correct functioning of the entire system (combination and integration of the respective devices).

This document defines tests to verify there will be no unintentional operation of the IAMS which could be caused by e.g. switching operation of built-in components.

It is important to consider the behaviour of the complete system when an internal arc occurs immediately after the assembly is energised.

Additionally, external influences in surrounding environment, e.g. sources of light, have to be considered.

The aim of the integration of the IAMS into PSC-assemblies is to reduce the released energy in case of an internal arc-fault by using the activation of an IARD in order to:

- reduce the damage to PSC-assemblies;

- improve the suitability of PSC-assemblies for further service after an internal arc-fault;
- improve the ability of PSC-assemblies to reduce the risk of injury to personnel;

The protection offered by an IAMS has some limitations. These are described in this document in the term "IAMS protected area" (verified within specific ranges of values for the rated operational voltage and the prospective short-circuit current) for the correct functioning of the IAMS.

IEC TR 61641 provides guidance for testing of PSC-assemblies with an integrated IAMS under conditions of arcing in air due to an internal fault and addresses personnel safety and damage to the PSC-assembly. Subclause 10.101.4 of this document (Verification of an IAMS in PSC-assemblies by test) is intended to be used in conjunction with IEC TR 61641.

INTEGRATION OF INTERNAL ARC-FAULT MITIGATION SYSTEMS IN POWER SWITCHGEAR AND CONTROLGEAR ASSEMBLIES (PSC-ASSEMBLIES) ACCORDING TO IEC 61439-2

1 Scope

This document states requirements for integration and testing of IAMS in low-voltage switchgear and controlgear assemblies – power switchgear and controlgear assemblies according to IEC 61439-1 and IEC 61439-2 (PSC-assemblies) to demonstrate their correct operation.

This document does not address personnel safety or damage to the PSC-assembly. These requirements are dealt with in IEC TR 61641 (see also 10.10.1).

NOTE This document can be used as a reference for other types of assemblies in the IEC 61439 series, but adaptation of the test procedures and acceptance criteria can apply taking into account the specifics of such other assemblies or products.

IAMS consist of IACDs and IARDs complying with their relevant product standard (e.g. optical based IACDs in accordance with IEC 60947-9-2, AQDs in accordance with IEC 60947-9-1 and SCPD's in accordance with IEC 60947-2). For the reliable function in a PSC-assembly, the verification of correct operation of the complete system under built-in conditions is addressed.

This document applies only to enclosed PSC-assemblies and deals with all required verifications needed for the integration in conjunction with IEC 61439-1 and IEC 61439-2.

The test procedure given in this document takes into consideration:

- the correct function of the IAMS within the PSC-assembly;
- the prevention of unintended operation of the IAMS within the PSC-assembly;
- the functioning behaviour of the system immediately after the assembly is energised.

Different tests under more severe conditions (e.g. doors in open position) can be performed with an agreement between the user and the original manufacturer of the PSC-assembly.

This document does not supersede any individual product standard. Individual devices are required to comply with their relevant standard.

This document does not apply to integration of arc fault detection devices (AFDD) according to IEC 62606.

The informative Annex II gives guidance on particular constructional requirements for incorporation of IAMS within a PSC-assembly.

The informative Annex HH gives guidance for the user of PSC-assemblies about the criteria to be considered when specifying a PSC-assembly with an integrated IAMS.

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.